



## HBC1001A-65

**Product code:** HBC1001A-65

**Manufacturer:** JL World

HBC1001A-65 is a JL World Noise-Canceling Condenser Microphone to convert sound into an electrical signal.

**Features:**

Dimensions: Ø9.7x5.2 mm

Rated Voltage: 1.5 V

Maximum Operating Voltage: 10 V

Frequency Range: 100~10000 Hz

Current Consumption:  $\leq 0.5$  mA

S/ Ratio:  $\geq 60$  dB

<b>Current Consumption (mA)</b>	$\leq 0.5$
<b>Impedance (<math>\Omega</math>)</b>	Low
<b>Frequency Range (Hz)</b>	100~10000
<b>S/N Ratio (dB)</b>	$\geq 60$
<b>Sensitivity (dB)</b>	$-45 \pm 3$
<b>Rated Voltage (V)</b>	1.5
<b>Typology</b>	Noise-Canceling