



## HMO1002B-62

**Product code:** HMO1002B-62

**Manufacturer:** JL World

HMO1002B-62 is a JL World Omni-directional Condenser Microphone to convert sound into an electrical signal.

**Features:**

Dimensions: Ø9.7x4.5 mm

Rated Voltage: 2 V

Maximum Operating Voltage: 10 V

Frequency Range: 50~15000 Hz

Current Consumption:  $\leq 0.5$  mA

S/ Ratio:  $\geq 60$  dB

<b>Current Consumption (mA)</b>	$\leq 0.5$
<b>Impedance (<math>\Omega</math>)</b>	$\leq 2200$
<b>Frequency Range (Hz)</b>	50~15000
<b>S/N Ratio (dB)</b>	$\geq 60$
<b>Sensitivity (dB)</b>	$-42 \pm 3$
<b>Operating temperature</b>	$-20 \sim +70$
<b>Rated Voltage (V)</b>	2
<b>Typology</b>	Omni-directional