



## HMO0603C-56

**Product code:** HMO0603C-56

**Manufacturer:** JL World

HMO0603C-56 is a JL World Omni-directional Condenser Microphone to convert sound into an electrical signal.

**Features:**

Dimensions: Ø6x2.9 mm

Rated Voltage: 3 V

Maximum Operating Voltage: 10 V

Frequency Range: 50~16000 Hz

Current Consumption:  $\leq 0.5$  mA

S/ Ratio:  $\geq 60$  dB

<b>Current Consumption (mA)</b>	$\leq 0.5$
<b>Impedance (<math>\Omega</math>)</b>	Low
<b>Frequency Range (Hz)</b>	50~16000
<b>S/N Ratio (dB)</b>	$\geq 60$
<b>Sensitivity (dB)</b>	$-36 \pm 3$
<b>Rated Voltage (V)</b>	3
<b>Typology</b>	Omni-directional