



HBO0602K-65

Product code: HBO0602K-65

Manufacturer: JL World

HBO0402D-62 is a JL World Omni-directional Condenser Microphone to convert sound into an electrical signal.

Features:

Dimensions: Ø6x1.6 mm

Rated Voltage: 2 V

Maximum Operating Voltage: 10 V

Frequency Range: 100~16000 Hz

Current Consumption: ≤ 0.5 mA

S/ Ratio: ≥ 58 dB

| | |
|--|------------------|
| Current Consumption (mA) | ≤ 0.5 |
| Impedance (Ω) | Low |
| Frequency Range (Hz) | 100~16000 |
| S/N Ratio (dB) | ≥ 58 |
| Sensitivity (dB) | -45 ± 3 |
| Rated Voltage (V) | 2 |
| Typology | Omni-directional |