

**Tecnosens S.p.A.** Via Vergnano,16 25125 Brescia (BS) Italia

Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it

## HCM0905BX

Product code: HCM0905BX Manufacturer: JL World

HCM0905BX is a JL World electromagnetic buzzer, PIN (self drive) mounting type.

Features: Dimensions: Ø9.6x5 mm Rated Voltage: 5 V Operating Voltage:  $3 \sim 7 V$ Rated Frequency:  $3100\pm300 \text{ Hz}$ Rated Current:  $\leq 30 \text{ mA}$ SPL (sound pressure level) at 10 cm:  $\geq 83 \text{ dB}$ 

Rated Current (mA)	≤30
Rated Frequency (Hz)	3100±300
SPL at 10 cm (dB)	≥83
Technology	Electro-Magnetic
Operating temperature	-40 ~ +85
Operating Voltage (V)	3~7
Туроlоду	Pin (Self Drive)

