

**Tecnosens S.p.A.** Via Vergnano,16 25125 Brescia (BS) Italia

Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it

## HPM14AX

Product code: HPM14AX Manufacturer: JL World

HPM14AX is a JL World piezoresistive buzzer, PIN (self drive) mounting type.

Features: Dimensions: Ø13.8x7.5 mm Rated Voltage: 12 V Operating Voltage:  $3 \sim 16$  V Rated Frequency: 4000 Hz Rated Current: <= 7 mA SPL (sound pressure level) at 10cm: >= 80 dB

Rated Current (mA)	≤7
Rated Frequency (Hz)	4000
SPL at 10 cm (dB)	≥ 80
Technology	Piezo
Operating temperature	-20 ~ +70
Operating Voltage (V)	3~16
Туроlоду	Pin (Self Drive)

