



HMO0603C-56

Product code: HMO0603C-56

Manufacturer: JL World

HMO0603C-56 is a JL World Omni-directional Condenser Microphone to convert sound into an electrical signal.

Features:

Dimensions: $\varnothing 6 \times 2.9$ mm

Rated Voltage: 3 V

Maximum Operating Voltage: 10 V

Frequency Range: 50~16000 Hz

Current Consumption: ≤ 0.5 mA

S/ Ratio: ≥ 60 dB

Current Consumption (mA)	≤ 0.5
Impedance (Ω)	Low
Frequency Range (Hz)	50~16000
S/N Ratio (dB)	≥ 60
Sensitivity (dB)	-36 ± 3
Rated Voltage (V)	3
Typology	Omni-directional