



HBO0603Z-53

Product code: HBO0603Z-53

Manufacturer: JL World

HBO0402D-62 is a JL World Omni-directional Condenser Microphone to convert sound into an electrical signal.

Features:

Dimensions: Ø5.8x2.2 mm

Rated Voltage: 3 V

Maximum Operating Voltage: 10 V

Frequency Range: 100~10000 Hz

Current Consumption: ≤ 0.5 mA

S/ Ratio: ≥ 70 dB

Current Consumption (mA)	≤ 0.5
Impedance (Ω)	Low
Frequency Range (Hz)	100~10000
S/N Ratio (dB)	≥ 70
Sensitivity (dB)	-33 ± 3
Rated Voltage (V)	3
Typology	Omni-directional