



HBO0403G-66S

Product code: HBO0403G-66S

Manufacturer: JL World

HBO0403G-66S is a JL World Omni-directional Condenser Microphone to convert sound into an electrical signal.

Features:

Dimensions: $\varnothing 4 \times 1.3$ mm

Rated Voltage: 3 V

Maximum Operating Voltage: 10 V

Frequency Range: 100~10000 Hz

Current Consumption: ≤ 0.5 mA

S/ Ratio: ≥ 60 dB

Current Consumption (mA)	≤ 0.5
Impedance (Ω)	Low
Frequency Range (Hz)	100~10000
S/N Ratio (dB)	≥ 60
Sensitivity (dB)	-46 ± 3
Rated Voltage (V)	3
Typology	Omni-directional