

Tecnosens S.p.A. Via Vergnano,16 25125 Brescia (BS) Italia

Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it

HC0901A Product code: HC0901A Manufacturer: JL World

HC0901A is a JL World electromagnetic buzzer, PIN mounting type.

Features: Dimensions: Ø9.5 x 5 mm Rated Voltage: 1.5 VOperating Voltage: $1 \sim 2 V$ Rated Frequency: 3200 HzRated Current: $\leq 80 mA$ SPL (sound pressure level) at 10 cm: $\geq 85 dB$

Coil Resistance (Ω)	5.5±1
Rated Current (mA)	≤80
Rated Frequency (Hz)	3200
SPL at 10 cm (dB)	≥ 85
Technology	Electro-Magnetic
Technology Operating temperature	Electro-Magnetic -20 ~ +60

