



Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it



HC0901F

Product code: HC0901F **Manufacturer:** JL World

HC0901F is a JL World electromagnetic buzzer, PIN mounting type.

Features:

Dimensions: Ø9.5 x 6.5 mm

Rated Voltage: 1.5 V

Operating Voltage: 1 ~ 2 V Rated Frequency: 3200 Hz Rated Current: <= 80 mA

SPL (sound pressure level) at 10cm: >= 80 dB

| Coil Resistance (Ω) | 5.5±1 |
|------------------------------|------------------|
| Rated Current (mA) | ≤80 |
| Rated Frequency (Hz) | 3200 |
| SPL at 10 cm (dB) | ≥ 80 |
| Technology | Electro-Magnetic |
| Operating temperature | -20 ~ +60 |
| Operating Voltage (V) | 1~2 |
| Rated Voltage (V) | 1.5 |
| Typology | Pin |

© Tecnosens S.p.A. 2025 1/1