

Tecnosens S.p.A. Via Vergnano,16 25125 Brescia (BS) Italia

Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it

HCM1612G

Product code: HCM1612G Manufacturer: JL World

HCM1612G is a JL World electromagnetic buzzer, PIN mounting type.

Features: Dimensions: Ø16.0x14.0 mm Rated Voltage: 12 V Operating Voltage: 6 ~ 18 V Rated Frequency: 2048 Hz Rated Current: <= 40 mA SPL (sound pressure level) at 10cm: >= 98 dB

Coil Resistance (Ω)	115 ± 15
Rated Current (mA)	≤40
Rated Frequency (Hz)	2048
SPL at 10 cm (dB)	≥ 98
Technology	Electro-Magnetic
Operating temperature	-40 ~ +85
Operating Voltage (V)	6~18
Туроlоду	Pin

