



HCM2606AX

Product code: HCM2606AX

Manufacturer: JL World

HCM2606AX is a JL World electromagnetic buzzer, PIN (self drive) mounting type.

Features:

Dimensions: Ø26.0x26.0x19.7 mm

Rated Voltage: 6 V

Operating Voltage: 4 ~ 8 V

Rated Frequency: 300~500 Hz

Rated Current: <= 35 mA

SPL (sound pressure level) at 10cm: >= 95 dB

Rated Current (mA)	≤35
Rated Frequency (Hz)	300~500
SPL at 10 cm (dB)	≥95
Technology	Electro-Magnetic
Operating temperature	-40 ~ +70
Operating Voltage (V)	4~8
Typology	Pin (Self Drive)