



Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it



HCS0503F

Product code: HCS0503F **Manufacturer:** JL World

HCS0503F is a JL World electromagnetic buzzer, SMD mounting type.

Features:

Dimensions: 5x5x2.5 mm

Rated Voltage: 3 V

Operating Voltage: 2 ~ 4 V Rated Frequency: 4000 Hz Rated Current: <= 100 mA

SPL (sound pressure level) at 10cm: >= 75 dB

Coil Resistance (Ω)	17 ± 3
Rated Current (mA)	≤100
Rated Frequency (Hz)	4000
SPL at 10 cm (dB)	≥75
Technology	Electro-Magnetic
Operating temperature	-20 ~ +60
Operating Voltage (V)	2~4
Typology	SMD

© Tecnosens S.p.A. 2025 1/1