



Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it



HCS0803D

Product code: HCS0803D **Manufacturer:** JL World

HCS0803D is a JL World electromagnetic buzzer, SMD mounting type.

Features:

Dimensions: 7.5x7.5x2.5 mm

Rated Voltage: 3 V

Operating Voltage: $2.5 \sim 4.5 \text{ V}$ Rated Frequency: 2900 HzRated Current: <= 100 mA

SPL (sound pressure level) at 10cm: >= 85 dB

Coil Resistance (Ω)	15 ± 3
Rated Current (mA)	≤100
Rated Frequency (Hz)	2900
SPL at 10 cm (dB)	≥ 85
Technology	Electro-Magnetic
Technology Operating temperature	Electro-Magnetic -40 ~ +85

© Tecnosens S.p.A. 2025 1 / 1