



# HCS1206A

**Product code:** HCS1206A

**Manufacturer:** JL World

HCS1206A is a JL World electromagnetic buzzer, SMD mounting type.

Features:

Dimensions: 12.8x12.8x10 mm

Rated Voltage: 6 V

Operating Voltage: 4 ~ 8 V

Rated Frequency: 2400 Hz

Rated Current:  $\leq 60$  mA

SPL (sound pressure level) at 10cm:  $\geq 85$  dB

<b>Coil Resistance (<math>\Omega</math>)</b>	47 $\pm$ 5
<b>Rated Current (mA)</b>	$\leq 60$
<b>Rated Frequency (Hz)</b>	2400
<b>SPL at 10 cm (dB)</b>	$\geq 85$
<b>Technology</b>	Electro-Magnetic
<b>Operating temperature</b>	-40 ~ +85
<b>Operating Voltage (V)</b>	4~8
<b>Typology</b>	SMD