




Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it



HCS1003FX

Product code: HCS1003FX **Manufacturer:** JL World

HCS1003FX is a JL World electromagnetic buzzer, SMD (self drive) mounting type.

Features:

Dimensions: 10x10x5.2 mm

Rated Voltage: 3 V

Operating Voltage: 2.5 ~ 5 V Rated Frequency: 2700±300 Hz Rated Current: <= 300 mA

SPL (sound pressure level) at 10cm: >= 80 dB

Rated Current (mA)	≤30
Rated Frequency (Hz)	2700±300
SPL at 10 cm (dB)	≥ 80
Technology	Electro-Magnetic
Operating temperature	-40 ~ +85
Operating Voltage (V)	2.5~5
Typology	SMD (Self Drive)

© Tecnosens S.p.A. 2024 1/1