



HMO1003A-60

Product code: HMO1003A-60

Manufacturer: JL World

HMO1003A-60 is a JL World Omni-directional Condenser Microphone to convert sound into an electrical signal.

Features:

Dimensions: $\varnothing 9.7 \times 6.7$ mm

Rated Voltage: 3 V

Maximum Operating Voltage: 10 V

Frequency Range: 50~16000 Hz

Current Consumption: ≤ 0.5 mA

S/ Ratio: ≥ 60 dB

Current Consumption (mA)	≤ 0.5
Impedance (Ω)	Bassa
Frequency Range (Hz)	50~16000
S/N Ratio (dB)	≥ 60
Sensitivity	-40 ± 3
Rated Voltage (V)	3
Typology	Omni-directional