

Tecnosens S.p.A. Via Vergnano,16 25125 Brescia (BS) Italia

Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it

HC0905F

Product code: HC0905F Manufacturer: JL World

HC0905F is a JL World electromagnetic buzzer, PIN mounting type.

Features: Dimensions: Ø9.5 x 6.5 mm Rated Voltage: 5 V Operating Voltage: $4 \sim 7 V$ Rated Frequency: 3200 Hz Rated Current: $\leq 80 \text{ mA}$ SPL (sound pressure level) at 10cm: $\geq 85 \text{ dB}$

Coil Resistance (Ω)	40 ± 4
Rated Current (mA)	≤80
Rated Frequency (Hz)	3200
SPL at 10 cm (dB)	≥ 85
Technology	Electro-Magnetic
Operating temperature	-20 ~ +60
Operating Voltage (V)	4~7
Туроlоду	Pin

