

**Tecnosens S.p.A.** Via Vergnano,16 25125 Brescia (BS) Italia

Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it

## HCM1206A

Product code: HCM1206A Manufacturer: JL World

HCM1206A is a JL World electromagnetic buzzer, PIN mounting type.

Features: Dimensions: Ø12.0x9 mm Rated Voltage: 6 V Operating Voltage: 4 ~ 8 V Rated Frequency: 2400 Hz Rated Current: <= 60 mA SPL (sound pressure level) at 10cm: >= 85 dB

Coil Resistance (Ω)	45 ± 5
Rated Current (mA)	≤60
Rated Frequency (Hz)	2400
SPL at 10 cm (dB)	≥85
Technology	Electro-Magnetic
Technology Operating temperature	Electro-Magnetic -40 ~ +85

