

**Tecnosens S.p.A.** Via Vergnano,16 25125 Brescia (BS) Italia

Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it



## **HCM1205F**

**Product code:** HCM1205F **Manufacturer:** JL World

HCM1205F is a JL World electromagnetic buzzer, PIN mounting type.

Features:

Dimensions: Ø12.0x6.5 mm

Rated Voltage: 5 V

Operating Voltage: 4 ~ 8 V Rated Frequency: 2400Hz Rated Current: <= 60 mA

SPL (sound pressure level) at 10cm: >= 85 dB

Coil Resistance (Ω)	45 ± 4
Rated Current (mA)	≤60
Rated Frequency (Hz)	2400
SPL at 10 cm (dB)	≥ 85
Technology	Electro-Magnetic
Operating temperature	-20 ~ +60
Operating Voltage (V)	4~8
Typology	Pin

© Tecnosens S.p.A. 2024 1/1