



Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it



HCM1612X

Product code: HCM1612X Manufacturer: JL World

HCM1612X is a JL World electromagnetic buzzer, PIN (self drive) mounting type.

Features:

Dimensions: Ø16.0x14.0 mm

Rated Voltage: 12 V

Operating Voltage: $8 \sim 15 \text{ V}$ Rated Frequency: $2300\pm300 \text{ Hz}$ Rated Current: <=30 mA

SPL (sound pressure level) at 10cm: >= 85 dB

Rated Current (mA)	≤30
Rated Frequency (Hz)	2300±300
SPL at 10 cm (dB)	≥75
Technology	Electro-Magnetic
Operating temperature	-30 ~ +85 °C
Operating Voltage (V)	8~15
Typology	Pin (Self Drive)

© Tecnosens S.p.A. 2024 1/1