



HCM2612AX

Product code: HCM2612AX

Manufacturer: JL World

HCM2612AX is a JL World electromagnetic buzzer, PIN (self drive) mounting type.

Features:

Dimensions: Ø26.0x26.0x19.7 mm

Rated Voltage: 12 V

Operating Voltage: 8 ~ 16 V

Rated Frequency: 300~500 Hz

Rated Current: \leq 35 mA

SPL (sound pressure level) at 10cm: \geq 95 dB

Rated Current (mA)	\leq 35
Rated Frequency (Hz)	300~500
SPL at 10 cm (dB)	\geq 95
Technology	Electro-Magnetic
Operating temperature	-40 ~ +70
Operating Voltage (V)	8~16
Typology	Pin (Self Drive)