



Tel: (+39) 030 3534144 Fax: (+39) 030 3530815 info@tecnosens.it PEC: tecnosens@legalmail.it



## HCM2612BX

**Product code:** HCM2612BX **Manufacturer:** JL World

HCM2612BX is a JL World electromagnetic buzzer, PIN (self drive) mounting type.

Features:

Dimensions: 26.0x26.0x19.5 mm

Rated Voltage: 12 V

Operating Voltage: 8 ~ 16 V Rated Frequency: 300~500 Hz Rated Current: <= 35 mA

SPL (sound pressure level) at 10cm: >= 95 dB

Rated Current (mA)	≤35
Rated Frequency (Hz)	300~500
SPL at 10 cm (dB)	≥95
Technology	Electro-Magnetic
Operating temperature	-40 ~ +70
Operating Voltage (V)	8~16
Typology	Pin (Self Drive)

© Tecnosens S.p.A. 2025 1/1