



HMO1002B-62

Product code: HMO1002B-62

Manufacturer: JL World

HMO1002B-62 is a JL World Omni-directional Condenser Microphone to convert sound into an electrical signal.

Features:

Dimensions: Ø9.7x4.5 mm

Rated Voltage: 2 V

Maximum Operating Voltage: 10 V

Frequency Range: 50~15000 Hz

Current Consumption: ≤ 0.5 mA

S/ Ratio: ≥ 60 dB

Current Consumption (mA)	≤ 0.5
Impedance (Ω)	≤ 2200
Frequency Range (Hz)	50~15000
S/N Ratio (dB)	≥ 60
Sensitivity (dB)	-42 ± 3
Operating temperature	$-20 \sim +70$
Rated Voltage (V)	2
Typology	Omni-directional