

DATE July 4, 2019 No. SV-70284-E

M	less	rs
1 7	ししつ	

# **SPECIFICATION**

### **Preliminary**

Semi	conduc	tor Pr	essure	Sensor

Model:	AL4 series (Differential Pressure Type)						
Project:							
Distributor:							
Reference:							

Yoshiyuki Uchiumi, Application Engineer Sensor Business Unit Electronic Component Business Company Fujikura Ltd.

Fujikura Ltd.

# **Table of Contents**

1.	Gene	eral			2
2.	Princ	iple			2
4.	RoHS	<b>3</b>			2
5.	Block	CDiagram and Pin	Connections		3
6.	Devic	ce Name Code			4
7.	Abso	lute Maximum Ra	tings		4
8.	Gene	eral Specifications			5
10.	Elect	rical Characteristic	es for I <sup>2</sup> C or SPI I	Interface	6
13.	I <sup>2</sup> C Co	ommunication Pro	tocol		7
14.	. I <sup>2</sup> C or SPI Circuits (Reference) . I <sup>2</sup> C Digital Interface . I <sup>2</sup> C Communication Protocol . SPI Digital Interface . SPI Communication Protocol . Output versus Input Pressure . Transfer Function . Device Marking . Soldering . Pressure Port Connection . Dimensions and Weights . Ordering Information . Tape & Reel Information . Handling Notes . Notes . Notes . pendix: Dimension Drawing 9-772-006 ALxxDB . Discription Preliminary  ble shown below is revision records of this specification		8		
15.	SPI C	ommunication Pro	otocol		8
	•	•			
17.	Trans	sfer Function			9
18.	Devic	ce Marking			10
19.	Solde	ering			10
		•			
22.	Orde	ring Information			11
	•				
24.	Hand	lling Notes			12
25.	Note	S			12
Appe	endix:	Dimension Drawin	ng		13
9-7	772-0	06 ALxxDB			13
Table	e sho	wn below is revisi	on records of th	his specification	1
			<u> </u>		
		ļ	<u> </u>		
			<u> </u>		
Es	št.	July 4, 2019	Y. Uchiumi	<del> </del>	
		Date	Name	Comment	Mark

#### 1. General

This document describes the specifications of the AL4 pressure sensors for differential pressure type.

# 2. Principle

Fujikura pressure sensor is composed of a silicon piezo-resistive pressure sensing chip and a signal conditioning integrated circuit. The low-level signal from the sensing chip is amplified, temperature compensated, calibrated, and finally converted to digital data that is proportional to the applied pressure.

# 3. Device Lineup

This device has the following lineup.

	Pressure	Supply						Pressu	re Ra	nge			
Model	Туре	Voltage	Accuracy	-10	-7	-4	-2	-1 0	1	2	4	7	10 kPa
	Туре	voitage		(-100)	(-70)	(-40)	(-20)	(-10)	(10)	(20)	(40)	(70)	(100) cmH <sub>2</sub> 0
AL4	Differential	5.0 Vdc 3.3 Vdc 3.0 Vdc	±1.5%FS					001KE 002KE 004KE 007KE					

### **Features**

- ✓ Digital output
- ✓ Low pressure
- ✓ High proof pressure
- ✓ Moisture sensitivity level (MSL) 1
- ✓ Low power consumption
- √ High accuracy
- ✓ Modification available


# **Applications**

- ✓ Battery-operated devices
- ✓ Medical devices
- ✓ Industrial pneumatic devices
- ✓ Consumer devices

### 4. RoHS

This device is compliant with the Restriction of the use of certain Hazardous Substances in Electrical and Electronic Equipment (RoHS).

# 5. Block Diagram and Pin Connections




Pin Assignment	Pi	n No.	Pin Name	I/O	Type	Function	
	1		NC	-	-	No connect	*
	2		NC	-	-	No connect	*
	3		NC	-	-	No connect	*
	4		NC	-	-	No connect	*
	5		NC	-	-	No connect	*
14 13 12 11 10 9 8	6		VSS	-	-	Common voltage connection	*
	7		VDD	-	-	Power supply connection	*
		o I <sup>2</sup> C	SDA	1/0	Digital	Serial bidirectional data	*
	8	SPI	SS	I	Digital	Slave select	
		I <sup>2</sup> C	SCL	I	Digital	Serial clock input	4
1 2 3 4 5 6 7	9	SPI	MISO	0	Digital	Master-In-Slave-Out	*
	4.0	I <sup>2</sup> C	NC	-	-	No connect	*
	10	SPI	SCLK	I	Digital	Serial clock input	
	11		NC	-	-	No connect	*
	12		NC	-	-	No connect	*
	13		NC	-	-	No connect	*
	14		NC	-	-	No connect	*

- \*1) Put a  $0.1\mu F$  capacitor between VDD Pin 7 and VSS.
- \*2) I<sup>2</sup>C or SPI is factory setting. User can not change communication mode.
- \*3) NC pins must be open.

#### 6. Device Name Code

The device name code is consisted of Sensor code, Pressure code, Slave address code and Packing style. For the exact ordering device number, please refer to Chapter 22 Ordering Information.



### Pressure Range Conversion (Reference)

Pressure Code	kPa	mbar	cmH₂O	inchH₂O	psi	mmHg
001KD	-1 - +1	-10 - +10	-10.1972 - +10.1972	-4.01865 - +4.01865	-0.145038 - +0.145038	-7.50062 - +7.50062
002KD	-2 - +2	-20 - +20	-20.3943 - +20.3943	-8.03729 - +8.03729	-0.290075 - +0.290075	-15.0012 - +15.0012
004KD	-4 - +4	-40 - +40	-40.7886 - +40.7886	-16.0746 - +16.0746	-0.580151 - +0.580151	-30.0025 - +30.0025
007KD	-7 - +7	-70 - +70	-71.3801 - +71.3801	-28.1305 - +28.1305	-1.01526 - +1.01526	-52.5043 - +52.5043
010KD	-10 - +10	-100 - +100	-101.972 - +101.972	-40.1865 - +40.1865	-1.45038 - +1.45038	-75.0062 - +75.0062

#### Note:

# 7. Absolute Maximum Ratings

ltem	Condition	Symbol		Rating		Unit	
item	Condition	Syllibol	Min.	Тур.	Max.	Offic	
Proof Pressure	Port A, B	Pmax	-	-	+100	kPa	*
Burst Pressure	Port A, B	Pburst	+100	-	-	kPa	*
Common Mode Pressure	Port A and B	Pcom	1	-	+100	kPa	*
Supply Voltage		VDDmax	-0.3	-	6	Vdc	
Voltage at Digital I/O pins		Vdiomax	-0.3	-	VDD+0.3	Vdc	
Operating Temperature		Topt	-40	-	+85	°C	
Storage Temperature		Tstg	-40	-	+85	°C	1

- \*1) Absolute maximum ratings are the limits that the device will withstand without damage.
- \*2) Proof Pressure is defined as maximum applied pressure to the device without damage.
- \*3) The device will be damaged, if applied pressure is beyond Burst Pressure.
- \*4) Common Mode Pressure is defined as maximum pressure applied to Port A and B simultaneously.

<sup>\*1)</sup> The device is calibrated based on the unit of "kPa". Other converted pressure values are for reference.

# 8. General Specifications

lk a ma		Condition	C. was bas l		Rating		Unit	
Item		Condition	Symbol	Min.	Тур.	Max.	Offic	
	6	AL40DB		4.75	5	5.25		1
Supply Voltage	Sensor Code	AL41DB	VDD	3.135	3.3	3.465	Vdc	*
	Code	AL42DB		2.85	3.0	3.15		
Type of Pressure			-	Differential pressure				*
Pressure Media			-	Non		*		
		001KD		-1	-	+1	kPa	
	Dunnan	002KD		-2	-	+2	kPa	*
Pressure Range	Pressure Code	004KD	Popt	-4	-	+4	kPa	*
	Code	007KD		-7	-	+7	kPa	
		010KD		-10	-	+10	kPa	
				-5	-	+65	°C	*
				-	-	95	%RH	*
				-	_	95	%RH	*
Dielectric Strength				-	-	1	mA	*
Insulation Resistance				100	-	-	МΩ	*

#### Notes:

- \*1) Supply voltage (VDD) should be constant.
- \*2) Differential pressure is defined as the difference between the pressure applied to Port A and that to Port B.
- \*3) Ensure the pressure media contains no particulates. The device is not compatible with liquids.
- \*4) Output is the difference between the pressure applied to Port A and the pressure applied to Port B. (Port A Port B)
- \*5) Pressure range is defined as the measurable pressure range of the device. Do not expose intentionally beyond minimum Popt and maximum Popt.
- \*6) Please also refer to Chapter 17 Transfer Function.
- \*7) Do not wet the device with dew.
- \*8) Dielectric strength is defined as the leakage current between all pins and the package with AC 500 V, 1 minute.
- \*9) Insulation resistance is defined as the resistance value between all pins and the package with DC 500 V.


### 9. Electrical Characteristics


Ambient temperature Ta=25°C

ltam		Condition	Cumbal		Rating		l loi+	
ltem		Condition	Symbol	Min.	Тур.	Max.	Unit	
Offset Pressure Data	Min. Popt, Port	A < Port B	Doff	598	819	1040	Count	*:
Balanced Pressure Data	Port A = Port B		Dbal	7971	8192	8413		*:
Full Scale Pressure Data	Max. Popt, Port	: A > Port B	Dfs	15344	15565	15786	Count	*,
Span Pressure Data	Min. to Max. Po	ppt	SD	-	14746	-	Count	*
Accuracy	F + CF%C		Error1	-1.5	-	+1.5	- %FS	*
	-5 to +65°C	Exclude Dbal error	Error2	-1.0	-	+1.0	/0Г3	*
Committee Comment	VDD = 5 Vdc	VDD = 5 Vdc		-	-	4.5	۸	*:
Supply Current	VDD = 3.3, 3.0 V	/dc	lc	-	-	3.5	mAdc	
Initializing Time	After VDD reac	ning 2.7 V	T <sub>INIT</sub>	-	-	10	msec.	*
Response Time	for reference		tr	-	1	-	msec.	*
		-5°C		-	461	-		
Temperature Data	for reference	+25°C	Dtmp	-	768	-	Count	*
, , , , , , , , , , , , , , , , , , , ,		+65°C		-	1177	-	1	

- \*1) Offset pressure data (Doff) is defined as the pressure data at minimum Popt.
- \*2) Balanced pressure data (Dbal) is defined as the pressure to Port A equals that to Port B.
- \*3) Balanced pressure data error is calibration error of Balanced pressure data (Dbal) at production. It does not include Long term drift. It would be suggested that applications have Auto-zeroing function.
- \*4) Full scale pressure data (Dfs) is defined as the pressure data at maximum Popt.
- \*5) Span pressure data (SD) is defined as the pressure data difference between Offset pressure data (Doff) and Full scale pressure data (Dfs).
- \*6) The unit of Accuracy "%FS" is defined as a percent error by Span pressure data (SD).

- \*7) Accuracy of Error1 consists of the following:
  - Non-linearity
  - Temperature errors over the temperature range -5 to 65°C
  - Pressure hysteresis
  - Error1: Calibration errors of sensitivity and offset
  - Error2: Exclude Calibration error of Balanced pressure (Auto-zeroing is required.)
- \*8) We can offer lower power mode products as modification product. Please ask Fujikura.
- \*9) Initializing process starts when VDD reached 2.7 V. After initializing process, ready to the operation.
- \*10) Response time (tr) is defined as the time for the change in the pressure data from 10 % to 90 % or from 90 % to 10 % of its final value when the input pressure makes a step change.
- \*11) Temperature Data (Dtmp) is for reference.





# 10. Electrical Characteristics for I<sup>2</sup>C or SPI Interface


Communication interface (communication mode) of  $I^2C$  or SPI is factory setting. User can not change communication mode like from  $I^2C$  to SPI or from SPI to  $I^2C$ .

Ambient temperature Ta=25°C

lhama		Condition	Ch. a.l		l lait	1		
Item	Condition		Symbol	Min.	Тур.	Max.	Unit	
Interface					I <sup>2</sup> C or SPI			*1
Input Low Voltage	C	AL40DB	VIL	0	-	1	V	
	Sensor Code	AL41DB		0	-	0.66	V	1
	Code	AL42DB		0	-	0.6	V	1
		AL40DB		4	-	5	V	1
Input High Voltage	Sensor Code	AL41DB	VIH	2.64	-	3.3	V	1
	Code	AL42DB		2.4	-	3	V	1
	Canaan	AL40DB		-	-	0.5	V	1
Output Low Voltage	Sensor Code	AL41DB	VOL	-	-	0.33	V	
	Code	AL42DB		-	-	0.3	V	

# Notes:

# 11. I<sup>2</sup>C or SPI Circuits (Reference)




<sup>\*1)</sup> I<sup>2</sup>C is a trademark of NXP Semiconductors.

# 12. I<sup>2</sup>C Digital Interface


lk a see	Condition	C. was la a l		Rating		l laste	
ltem	Condition	Symbol	Min.	Тур.	Max.	Unit	
SCL clock frequency		$f_{SCL}$	100	-	400	kHz	1
Start condition hold time rela	t <sub>HDSTA</sub>	0.1	-	-	μsec.	1	
Minimum SCL clock low widt	h	t <sub>LOW</sub>	0.6	-	-	μsec.	*2
Minimum SCL clock high wid	t <sub>HIGH</sub>	0.6	-	-	μsec.	*2	
Start condition setup time re	t <sub>susta</sub>	0.1	-	-	μsec.	1	
Data hold time on SDA relati	ve to SCL edge	t <sub>HDDAT</sub>	0	-	-	μsec.	1
Data setup time on SDA relat	tive to SCL edge	t <sub>SUDAT</sub>	0.1	-	-	μsec.	1
Stop condition setup time or	SCL	t <sub>susto</sub>	0.1	-	-	μsec.	
Bus free time between stop	condition and start condition	t <sub>BUS</sub>	2	-	-	μsec.	1
Load Capacitance	Pin8 SDA, 400kHz	Cmax	-	-	200	pF	1
Pull-up Resistor Pin8 SDA, Pin9 SCL		Rpu	1	-	-	kΩ	1
Slave address			0x28 to 0x7	8		*3	

### Notes:

- \*1) There are three differences in this device protocol compared with the original  $I^2C^{TM}$  protocol:
  - Sending a start-stop condition without any transitions on the CLK line (no clock pulses in between) creates a communication error for the next communication, even if the next start condition is correct and the clock pulse is applied. An additional start condition must be sent, which results in restoration of proper communication.
  - The restart condition a falling SDA edge during data transmission when the CLK clock line is still high creates the same situation. The next communication fails, and an additional start condition must be sent for correct communication.
  - A falling SDA edge is not allowed between the start condition and the first rising SCL edge. If using an I2C™ address with the first bit 0, SDA must be held low from the start condition through the first bit.
- \*2) Combined low and high widths must equal or exceed minimum SCLK period.
- \*3) Slave address is factory setting. Customer can not change the slave address.



# 13. I<sup>2</sup>C Communication Protocol



- \*1) If the status bits are 01, the device must be re-started to turn power supply off and on again.
- \*2) If a data fetch is performed before or during the first measurement after power-on reset, then "stale" will be returned, but this data is actually invalid because the first measurement has not been completed.
- \*3) If the status bits are 11, do not use the device anymore.


# 14. SPI Digital Interface

This mode is half duplex (read-only).

ltem	Condition	Symbol	Symbol		Unit		
item	Condition	Зуппоот	Min.	Тур.	Max.	Unit	
SCLK clock frequency	4 MHz clock	$f_{SCL}$	50	-	800	kHz	
SS drop to first clock edge		t <sub>HDSS</sub>	2.5	-	-	μsec.	
Minimum SCLK clock low width		t <sub>Low</sub>	0.6	-	-	μsec.	*1
Minimum SCLK clock high width		t <sub>HIGH</sub>	0.6	-	-	μsec.	*1
Clock edge to data transition		t <sub>CLKD</sub>	0	-	0.1	μsec.	
Rise of SS relative to last clock edge		t <sub>suss</sub>	0.1	-	-	μsec.	
Buss free time between rise and fall of SS		t <sub>BUS</sub>	2	-	-	μsec.	

### Notes:

### **Timing Diagram**



# 15. SPI Communication Protocol

The master should sample MISO on the rise of SCLK.

Item	Measurement Packet				
Data Fetch	SCLK  MISO  Hi-Z  S1  S0  P13  P12  WP7  P6  WP0  T10  T9  WT1  T0  X  Hi-Z  SS  Packet = [{S(1:0),B(13:8)},{B(7:0)},{T(10:3)},{T(2:0),xxxxx}}]  S(1:0) = Status bits of packet (Normal, Command, Busy, EEPROM Error)  P(13:8) = Upper 6 bits of 14-bit pressure data  P(7:0) = Lower 8 bits of 14-bit pressure data  T(10:3) = Corrected temperature data (if application does not require corrected temperature data, terminate read only.)  T(2:0),xxxxx = Remaining bits of corrected temperature data for full 11-bit resolution  Hi-Z = High impedance				

<sup>\*1)</sup> Combined low and high widths must equal or exceed minimum SCLK period.


# 16. Output versus Input Pressure

Pressure Code	Output vs. Input pressure
	Temp. = -5 to 65°C
001KD 002KD 004KD 007KD 010KD	Doff: 819  Port A < Port B  Port A > Port B  Input Pressure  Port A > Port B  Input Pressure

# 17. Transfer Function

Item	Transfer Function					
	Pressure Data (Count) = $P \times \alpha + \beta \pm$ (Error1 × Temperature Error Multiplier) $P (kPa) = \frac{Pressure \ Data - \beta \pm (Error1 \times Temperature \ Error \ Multiplier)}{\alpha}$					
	Pressure Code	P (kPa)	α	β	Error1	
	001KD	-1 to +1	7373	8192	221	
_	002KD	-2 to +2	7373/2	8192	221	
Pressure	004KD	-4 to +4	7373/4	8192	221	
Data	007KD	-7 to +7	7373/7	8192	221	
	010KD	-10 to +10	7373/10	8192	221	
	Error Multiplier 2 3 4 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5	20 0 T	20 emperature (°C)	40 60	80	
Temperature Data	Dtmp (Count) =	2047 200 × (T + 50)	<> T(	$(^{\circ}C) = \frac{200}{2047} \times Dtn$	np - 50	


### 18. Device Marking



Notes:


- \*1) Port option is not marked on the package.
- \*2) Custom ID will be added when product is customized for a customer.

### 19. Soldering



- \*1) This device is classified as moisture sensitivity level (MSL) 1 that is defined in Jedec standard J-STD-20. Floor life time is unlimited. However, the plating of pins is silver (Ag) that could be discolored to black or brown by sulfur in the environment. Discoloration of pins could impact soldering reliability. The device should be sealed in the embossed carrier tape before soldering.
- \*2) NEVER wash the device with any washing liquid. NEVER wash the device with any ultrasonic washing machine.
- \*3) Do not put the solder and flux on the device's package.
- \*4) Temperature means Surface temperature of the device's package.
- \*5) Do not reflow more than twice.

#### 20. Pressure Port Connection



# **Recommended Tube (Reference)**


Flexible tubing is recommended. The following tubing is for reference. Please select appropriate tubing considering material, Durometer hardness and maximum pressure.

Manifold connection can also be available with O-ring or sealing fixtures.

I.D.	O.D.	Wall thickness
3/32 inch	7/32 inch	1/16 inch
2 mm	4 mm	1 mm

### **Manifold Connection (Reference)**

Manifold connection can also be available with O-ring or sealing fixtures. There are parting lines on the surface of the pressure port at the base side. Top part of the pressure port (barbed part) is recommended for sealing with fixtures.



# 21. Dimensions and Weights

Refer to the following drawing as attached. 3D CAD model is available. Please ask Fujikura distributor.

Sensor Code	Dimension Drawing	Weight
AL4xDB	9-772-006	approx. 0.55 grams

# 22. Ordering Information


Model	Package	Supply Voltage	Packing	Ordering Device Number	Qty./Packing	
		5.0 Vdc	Tape & Reel	AL40DB-[Pressure Code]-[Com Mode]-TP	500	Pcs/Reel
AL4 SMD	3.3 Vdc	Tape & Reel	AL41DB-[Pressure Code]-[Com Mode]-TP	500	Pcs/Reel	
		3.0 Vdc	Tape & Reel	AL42DB-[Pressure Code]-[Com Mode]-TP	500	Pcs/Reel

Pressure Range Pressure Code Communication Mode 001KD +1 kPa 0x28 -1 to -2 +2 kPa 002KD 0x38 3 to 004KD  $I^2C$ +4 kPa 0x48 -4 to 4 -7 to +7 kPa 007KD Slave address 0x58 5 -10 010KD to +10 kPa 0x68 6 0x78 7 S

I2C or SPI is factory setting.

User can not change the communication mode.

# 23. Tape & Reel Information



# 24. Handling Notes

Plating of pins is silver (Ag). Silver has physical property that is discolored to black or brown by sulfur. There are notes for handling as below:

- · To prevent discoloration of pins, please keep the devices sealed in static shielding bags before soldering.
- Do not solder the devices that have discolored pins.
- After soldering, pins would be discolored in black or brown in atmosphere. However it does not impact reliability of the device.

### 25. Notes

- Fujikura reserves all rights.
- · This document is subject to change without notice.
- · Limitation, usage, environment, standard warranty and so on are listed on Fujikura web site.
- · Please refer to the latest specifications.

